



3 LONGHORSE 3

LH3-120-L

BALLAST SPECIFICATIONS

UL & cUL APPROVED (E186503) • PATENTED

INPUT


VOLTAGE	120 ± 10% VAC
FREQUENCY	50/60 Hz
MAXIMUM POWER	64 WATT
MAXIMUM CURRENT	.61 AMP
PROTECTION	
• OVER CURRENT	FUSE
• VOLTAGE TRANSIENTS	MOV (PER ANSI C82.11 - 1993)
EMI /RFI	FCC PART 18-A

OUTPUT

OPEN CIRCUIT VOLTAGE	600V RMS MAXIMUM
BALLAST MIN. STARTING TEMP	-20°F
LAMP STARTING / TEMP	INSTANT START / SEE LAMP SPECIFICATIONS
PROTECTION	
• OPEN LAMP	YES
• SHORTED LAMP	YES

APPLICATION / MECHANICAL

RATED		TYPE 1 OR 2 OUTDOOR
BLACK / WHITE WIRES	"L"	18 INCHES
RED / YELLOW POWER WIRES	"L"	36 INCHES
BALLAST SIZE	"L"	H 1", W 1 3/4", L 9 1/2"
BALLAST WEIGHT		14.4 OZ
CASE QUANTITY		50 BALLASTS
CASE WEIGHT		45 lbs



LAMP COVERAGE

WHEN OPERATED IN ACCORDANCE WITH FULHAM'S WIRING CONFIGURATIONS

LINEAR LAMPS	ONE OR MORE LAMPS	ONE LAMP ONLY
T-5 HO	F24	F39 or F54
T-6	F42	
T-8	F13, F15, F17, F25, F30 or F32	F14, F18, F30 or F40
T-8 HO		F40, F60 OR F72
T-10		F40
T-12	F15	F14, F20, F25, F30, F36, F40, F42, F48, F60, F64, F72 or F84

Fulham Co., Inc.

10/27/2008
www.Fulham.com

12705 South Van Ness Ave.

TEL: 1.323.779.2980

Hawthorne, CA 90250

FAX: 1.323.754.9060

info@fulham.com

3 LONGHORSE 3

COMPACT LAMPS

BX	13W, 18W or 24W	27W, 28W, 36W, 39W, 40W, 50W or 55W
FQD	24W	18W, 28W or 36W
QD	18W or 26W	
TB	18W	26W, 32W or 42W
2D	21W or 28W	38W
CIRCLINE		20W, 22W, 32W, 40W or 22W+32W
T-5 CIRCLINE		22W, 40, 55W or 22W+40W

Fulham Co., Inc.

10/27/2008
www.Fulham.com

12705 South Van Ness Ave.

TEL: 1.323.779.2980

Hawthorne, CA 90250

FAX: 1.323.754.9060

info@fulham.com