



6 LONGHORSE 6

LH6-277-L

BALLAST SPECIFICATIONS

UL & cUL APPROVED (E186503) • PATENT PENDING

INPUT

VOLTAGE 277 $\pm$ 10% VAC
 FREQUENCY 50/60 Hz
 MAXIMUM POWER 140 WATT
 MAXIMUM CURRENT .50 AMP

PROTECTION

- OVER CURRENT
 - VOLTAGE TRANSIENTS
- EMI /RFI

FUSE

MOV (PER ANSI C82.11 - 1993)
 FCC PART 18-A


OUTPUT

OPEN CIRCUIT VOLTAGE 600V RMS MAXIMUM
 BALLAST MIN. STARTING TEMP -20°F
 LAMP STARTING / TEMP INSTANT START / SEE LAMP SPECIFICATIONS
 PROTECTION

- OPEN LAMP YES
- SHORTED LAMP YES

APPLICATION / MECHANICAL

RATED TYPE 1 OR 2 OUTDOOR
 BLACK / WHITE WIRES 18 INCHES
 RED POWER WIRES 36 INCHES
 YELLOW POWER WIRE 36 INCHES
 BALLAST SIZE H 1", W 1-3/4", L13.3"
 BALLAST WEIGHT 27.2 OZ
 CASE QUANTITY 25 BALLASTS
 CASE WEIGHT 42.5 lbs



LAMP COVERAGE

WHEN OPERATED IN ACCORDANCE WITH FULHAM'S WIRING CONFIGURATIONS.

LINEAR LAMPS

T-5

ONE OR MORE LAMPS

F4, F6, F8, F13, F14, F21, F28 OR
 F35

ONE LAMP ONLY

T-5 HO

F24 OR F39

F54 OR F80

T-6

F42 OR F64

T-8

F13, F14, F15, F17, F18, F25, F30,
 F40 OR F72

F70

T-8 HO

F48, F60 OR F72

T-10

F40

T-12

F14, F15, F20, F24, F30, F36, F40,
 F48, F60, F64, F72, F84 or F96
 (60W)

F25, F96(75W/60W)

Fulham Co., Inc.

10/27/2008

12705 South Van Ness Ave.

TEL: 1.323.779.2980

www.Fulham.com

Hawthorne, CA 90250

FAX: 1.323.754.9060

info@fulham.com

6 LONGHORSE 6

T-12 HO		F18, F24, F30, F36, F42, F48, F60, F64, F72, F84 or F96
<i>COMPACT LAMPS</i>	<i>ONE OR MORE LAMPS</i>	<i>ONE LAMP ONLY</i>
BX	24W, 27W, 36W or 40W	28W, 39W, 50W or 55W
FQD	32W	55W
QD	13W, 18W or 26W	27W
TB	13W, 18W, 26W, 32W or 42W	
2D	16W, 21W, 28W or 38W	
CIRCLINE		22W + 32W
T-5 CIRCLINE	22W or 40W	22W + 40W

Fulham Co., Inc.

10/27/2008
www.Fulham.com

12705 South Van Ness Ave.
Hawthorne, CA 90250

TEL: 1.323.779.2980

FAX: 1.323.754.9060

info@fulham.com