

C218UNVSV3ME

APPLICATION and PERFORMANCE SPECIFICATION

Description: High frequency dimming electronic ballast for (2) CFQ/TR18W lamps

Secondary Applications: (1) CFQ/TR18W

- Line voltage: 120vac to 277vac, $\pm 10\%$, 50-60Hz
- Auto Reset End of Lamp Life Shutdown Circuitry
- Series lamp operation
- Programmed rapid start
- Active power factor correction

Lamp		Input Voltage	Max/Min		Min Start Temp °F/°C	Full Bright			
Type	Qty		Ballast Factor	Input Power [Watts]		Line Current [Amps]	Max Thd [%]	Crest Factor	BEF
CFQ/TR18W	2	120	1.00/.03	39 / 10	32/0	0.33	< 10	1.7	2.56
CFQ/TR18W	2	277	1.00/.03	38 / 10	32/0	0.15	< 10	1.7	2.63
CFQ/TR18W	1	120	1.00/.03	20 / 5	32/0	0.17	< 10	1.7	5.00
CFQ/TR18W	1	277	1.00/.03	20 / 6	32/0	0.08	< 10	1.7	5.00

Data taken at 100% Light Level unless otherwise noted.

Application and operation performance specification information subject to change without notification.

Performance:

- Meets ANSI Standard C82.11
- Meets ANSI Standard C62.41
- Meets FCC Part 18 for EMI and RFI Non-Consumer Limits

Safety:

- No PCB's
- cUL-us LISTED (Class P, Type 1 Outdoor, Type CC)

Application:

- Minimum starting temperature: 32° F, 0° C
- Maximum case temperature: 167° F, 75° C
- Sound rating: Class A
- Remote mounting: 18"
- Line voltage protection for control circuit
- Dimming range: 100% to 3% light output
- Line voltage protection for control circuit
- Maximum lead lengths: Red: 18"
Blue: 18"
Yel: 18"

Physical Parameters:

- Overall length: 4.94"
- Mounting length: 4.61"
- Width: 3.00"
- Height: 1.00"
- Weight: .60 lbs
- Carton Quantity 20
- Lead entry: ME - Side and Bottom Access

- Please review the SuperDim Application Notes at

<http://www.universalballast.com/techSupport/application-notes/superdim/index.html>

Warranty:

- Universal Lighting Technologies warrants to the purchaser that each electronic ballast will be free from defects in material or workmanship for a period of (5) years from date of manufacture when properly installed and under normal conditions of use. Call 1-800-BALLASTx800 for technical assistance.

Dimming Control Specifications:

- 10 to 0 vDC Voltage Control
- 10v = maximum output
- 0v = minimum output
- Built-in line voltage protection circuit: Deep-dimming condition when line voltage is applied to control leads
- Can be wired as Class 1 or Class 2 Circuit
- Ballast will source a maximum of 250uA for control needs

Manufactured in North America

Ballast must be grounded in accordance with national and local electrical codes

Control Wiring

- Use Purple (+) & Gray (-) for connection to 0-10vDC.
- Ballast protected if line voltage is applied.
- Wiring Purple & Gray together provides 3% light output.
- Capping Purple & Gray separately provides 100% light output.

