

## Lytecaster® Recessed Downlighting 1100FTUES

Page 1 of 1

6 3/4" Aperture 1 Light, 120V 26/32W Triple Tube Fluorescent Frame-In Kit









Reflector Trim Note: Ballast is 120V only

Complete Fixture consists of Reflector Trim & Frame-In Kit.

| Frame-In Kit |         |                               | Reflector Trims — See Individual Reflector Trim Specification Sheets |  |                                  |   |                |             |  |  |
|--------------|---------|-------------------------------|--|--|----------------------------------|---|----------------|-------------|--|--|
|              |         |                               | Open Downlight   |  |                                  |   |                |             | Enclosed   | Wall   |
|              | Voltage | Lamp                          | Reflector  | Cone   | Satin Cone                       | Baffles   | Basic White    | Cross Blade | Diffusers  | Washer   |
| 1100FTUES    | 120V    | 26W and<br>32W<br>triple tube | 1143<br>1144<br>1144CD<br>1145<br>1146<br>1146CD                     | 1112<br>1112NM<br>1113<br>1113BK<br>1113CD<br>1113WH<br>1113NM<br>1113CDNM | 1108<br>1108NM<br>1110<br>1110NM | 1105<br>1105WH<br>1105BNM<br>1105NM<br>1176<br>1176WH<br>1179M1<br>1179WH | 1171<br>1170M1 | 1132        | 1121<br>1124<br>1126<br>1128<br>1134<br>1177SH<br>1178SH<br>1190 | 1135<br>1135WH<br>1185<br>1186<br>1186WH<br>1195<br>1196 |

## **Features**

- Mounting Frame: 0.036" (#20 ga.) galvanized steel. Accommodates all ceilings up to 1" thick; including existing or inaccessible areas. Breakout section and anchor nails for existing ceilings. Push-in/twist-out rotoclips hold reflector flush to ceiling.
- 2. Junction Box: 0.063" (#14 ga.) 4" x 3 1/2" x 2" galvanized steel. U.L. listed for maximum of 8 No. 12 ga., 75°C through branch circuit conductors. Integral cable clamps permit attachment of nonmetallic Romex® or Armored cable without the need for separate connectors.
- 3. Mounting Bars: 0.059" (#16 ga.) galvanized steel. 13" long bars extend to 27", rotatable and lockable, with integral T-bar tabs. Attaches to wood joist or T-bar ceilings without need of accessories.
- $\textbf{4. Socket Housing:} \ \textbf{Steel precisely attached to reflector by spring clip.}$
- Socket: Four-pin base, molded thermoplastic. Prewired with No. 18 AWM leads to junction box.
- 6. Ballast: Electronic 120V, end of lamp life protected, FCC class "B" consumer limits, class "A" sound rating. Energy Star® qualified. Insulation must be kept 3" away from fixture sides and wiring compartment and must not be placed above fixture in a manner which will entrap heat.

## **Electrical**

|                | 26W                    | 32W  |
|----------------|------------------------|------|
| Input Volts:   | 120V                   | 120V |
| Input Watts:   | 29                     | 36   |
| Amps:          | .24                    | 0.31 |
| Minimum starti | ng temperature is 0°F. |      |

**Options & Accessories** 

**Mounting Bars:** 1964 - 20" set of (2)

T-Bar Anchor Clips: 1956 - set of (4) for use with above bars Concealed Spline Ceiling Kit: 1965 - set of (4), 1 1/2" to 2 1/2" Mtg. Ht.

Plaster Ceiling Ring: 1960 - 7/8" depth for wet plaster ceilings.

Extra-Thick Ceiling Mounting Ring: 1967A - up to 2" thick ceilings.

Remodeler Anchor Clip: 1985S

## l ahels

UL (Suitable for Damp Locations), I.B.E.W.

Romex® is a registered trademark of General Cable Industries Inc.

US Patent No's.: 5,045,985

| Job Information | Туре: |
|-----------------|-------|
| Job Name:       |       |
| Cat. No.:       |       |
|                 |       |
| Lamp(s):        |       |
| Notes:          |       |
|                 |       |
|                 |       |

**Lightolier** a Genlyte company www.lightolier.com 631 Airport Road, Fall River, MA 02720 • (508) 679-8131 • Fax (508) 674-4710 We reserve the right to change details of design, materials and finish. © 2006 Genlyte Group LLC • C0906