# **PRODUCT SPECIFICATIONS:**

# **Fixtures:**

- Line voltage LED Lightbars are constructed of high quality extruded aluminum
- Durable powder-coated finish ensures a sleek appearance in all installations
- Architectural-grade diffuser eliminates unsightly hot spots and ensures an even, pleasing distribution of light

# **LED Module:**

 High-ranked binning of LM-80 rated LEDs for crisp white light and color uniformity

## Installation:

- Easy installation with pressure clips and double-sided tape
- Hardwire and plug-in configurations allow the Lightbars to adapt installation needs for any situation
- Additional tools not required for most installations

# Driver:

• Integral low-voltage driver – no additional external ballast or driver needed

# **Photometrics:**

• Visit www.maxlite.com for complete **photometric** and IES files for LED Lightbars

# Warranty:

• Backed by MaxLite's five-year limited warranty

# LIGHTBAR ORDERING:

Watts	Order Code	Model Number	Delivered Lumens	Lamp Life (Hrs.)	Dimensions (L"xW"xH")	ССТ
3.1	71217	MLSDLB9627LED	125	50,000	6 x 0.79 x 0.84	2700
3.1	72046	MLSDLB9635LED	135	50,000	6 x 0.79 x 0.84	3500
3.1	71218	MLSDLB9650LED	152	50,000	6 x 0.79 x 0.84	5000
3.6	71215	MLSDLB1227LED	181	50,000	12 x 0.79 x 0.84	2700
3.6	72044	MLSDLB1235LED	190	50,000	12 x 0.79 x 0.84	3500
3.6	71216	MLSDLB1250LED	198	50,000	12 x 0.79 x 0.84	5000
6.1	71213	MLSDLB1827LED	285	50,000	12 x 0.79 x 0.84	2700
6.1	72045	MLSDLB1835LED	300	50,000	12 x 0.79 x 0.84	3500
6.1	71214	MLSDLB1850LED	312	50,000	12 x 0.79 x 0.84	5000
8.6	71211	MLSDLB3327LED	467	50,000	12 x 0.79 x 0.84	2700
8.6	72043	MLSDLB3335LED	480	50,000	12 x 0.79 x 0.84	3500
8.6	71212	MLSDLB3350LED	503	50,000	12 x 0.79 x 0.84	5000

## **ACCESSORIES INCLUDED:**







4" corner joiner for continuous runs

Quick-clip mounting bracket and screws Bar-to-bar joiner

• Alternative mounting option: double sided tape is also included with every lightbar

# **ACCESSORIES SOLD SEPARATELY:**

Order Code	Model Number	Description
71219	MLSDLBJL40G	Joiner lead 40" with 2 plugs
71221	MLSDLBJL70G	Joiner lead 70" with 1 plug hard wire
71225	MLSDLBLC48G	Line cord 48" w/ molded plug for demonstrating
71631	MLSDLBCONNS	Lightbar connection box - unpainted
71645	MLSDLBCONNSW	Lightbar connection box - painted



71219- MLSDLBJL40G



71221- MLSDLBJL70G







71225- MLSDLBLC48G

71631- MLSDLBCONNS - Unpainted 71645- MLSDLBCONNSW - Painted

# DISTRIBUTOR / REPRESENTATIVES

OR CONTACT MAXLITE: 1-800-555-5629 info@maxlite.com | www.maxlite.com











**LED PLUG-AND-PLAY** 

Dimmable

**LIGHTBARS** 



**LED Lightbars For** 

**Home, Office and** 

**Hospitality** 





# DO IT YOURSELF



MaxLite's LED Plug-and-Play Lightbars are dimmable accent, under cabinet, and indirect lighting fixtures featuring high lumen output and an integral driver that plugs directly into existing 120-volt systems. Part of the MaxLED® family of products, MaxLite's LED Lightbars are available in 3.1- to 8.6-watts.

Constructed with propriety binned LM-80-rated LED chips for color consistency, the LED Lightbars have a long-lasting life of up to 50,000 hours.

The self-driven LED lightbars feature a diffuser cover that minimizes glare and delivers even light in commercial and residential applications, including bathrooms, conference rooms and lobbies, factory workspaces, and foyers in homes, retailers, restaurants, hotels and other commercial and hospitality venues.

# **LED Lightbars Enlighten Dreary Spaces**




MaxLite's Plug-and-Play LED Lightbars were featured on the "Bath Crashers" on the DIY Network, from the makers of HGTV. On Episode 404 "Basement Bathroom Overhaul," MaxLite's LED Lightbars

were professionally installed discreetly in three handmade light boxes that were installed on the bathroom wall, and in the countertop of the bathroom vanity, which made the glass surface glow above. With the use of MaxLite's LED Lightbars, the bathroom now yields a brightly-lit, clean modern look.

# MaxLite's LED Plug-and-Play Lightbars' key features include:

- Available in 2700K, 3500K or 5000K CCTs in six-inch and one-foot lengths
- Dimmable from 100 down to 15 percent
- Connect up to 30 (8.6 watt) LED Lightbars in a single run
- Hardwire or plug-and-play installations
- Diffuser eliminates hot spots and ensures even light distribution
- Dry-location listed
- Long 50,000-hour life
- Leading efficacy is superior to CFL and halogen fixture alternatives
- Mounting clips, double sided tape, connectors and linking cables included

# LIFE:



Life: 50,000 hour life is based on L70 standards. When the LEDs' lumen output depreciates by 30 percent, end-of-life is reached, even though the lamp will still provide approximately 70 percent of initial lumens.

# **APPLICATIONS:**

MaxLite's Plug-and-Play LED Lightbars are ideal for residential and commercial environments including:



New Jersey homeowner installation

### Residentic

For under base cabinet and other installations where the light source is hidden from view, the LED Lightbars create a brightly lit room with indirect illumination in kitchens and dining areas.


# **Hospitality:**

The LED Lightbars enable continuously lit long runs to accent coves and highlight the architectural integrity of hospitality rooms and lobbies.



# Bar and Lounge:

To showcase and accent a room's key features, MaxLite's LED Lightbars provide cool operation to enlighten under base cabinets, toe kicks and other elements in retailers and restaurants.



### Libraries:

The LED Lightbars come with a diffuser that minimizes glare and delivers even light distribution while concealing the LEDs from view in library wall and ceiling coves and moldings.

