

Product Deta	ils		Specification Features	
Description:	Line voltage track head for use with WAC brand H, L, J & J2 series track systems. In addition it may fit other manufacturer's original track (consult factory for specific brands).		 Classic open "flatback" style track head provides maximum installation convenience with its ability to work on four different 	
Materials:	Metal track head and mounting bracket with polycarbonate aiming knob and track adaptor. Medium base 250V porcelain socket with nickel-plated copper screw shell.		track systems.	
Aiming:	350° horizontal rotation and 90° vertical aiming.		 The 188 series utilizes the second circuit of J2 track with the use of the optional JClip. 	
Lamping:	Uses medium base PAR16, PAR20, PAR30, PAR38, R, G, or A style lamps, 150W max. 120 volt. Lamps sold separately.	.	 Track head extensions are available for the H system. 	
Systems:	HTK is used with the WAC H system track (HT) JTK is used with the WAC J system and J2 system track (JT & J2-T) LTK is used with the WAC L system track (LT)		Extension lengths are 18", 24", 36" and 48". Available in Black (BK) or White (WT).	
Finish:	Available in Black (BK), White (WT), Brushed Nickel (BN), Dark Bronze (DB)		 Barn doors are available for the PAR20, PAR30 and PAR38 lamps. Order as PAR20BD, 	
Listing:	UL & CUL Listed. 5 year WAC Lighting product warranty.		PAR30BD, or PAR38BD.	

Compatible Accessories										
JCLIP Ordered when using track heads on 2 nd circuit of J2 style track.		Line Voltage Extension Extend HTK-188 track heads. Order as one of the following;			Barn Doors Snap onto PAR lamps to help direct light output. Available in BK, BN or WT.					
		H18-color	H24-color		Available III BR, BN 01 WT.					
Order as JCLIP		H36- <mark>color</mark>	H48-color		Order as PARsizeBD-color					

WAC Lighting reserves the right to modify the design of our products as part of our continuous improvement program.